

Crimp Reference Guide

Crimp Set	Hex Dimensions (Outer Conductor)	Hex/Square Dimensions (Centre Conductor)	Typical Cable Sizes Using Crimp Set
A	5.41	1.69	RG58, 9001, 9006, RG142, RG223, RG400
B	6.48	1.69	RG59, RG62
C	10.54	2.54	RG213
D	10.9	2.54	RG214, RG63
E	3.25	0.72	RG174, RG63, RG179

Cable Type	Hex <i>inch</i>	Centre Crimp <i>mm</i>	Centre Crimp <i>inch</i>	Length <i>mm</i>	Tool-HT-330K
RG58C/U	0.213	1.69	0.067	8	A or G
RG59C/U	0.255	1.69	0.067	8	A or G
RG62A/U	0.255	1.69	0.067	8	A or G
RG63B/U	0.429	2.54	0.100	10	K
RG142B/U	0.213	1.69	0.067	8	A or G
RG174A/U	0.128	0.72	0.028	8	J outer only
RG178B/U	0.105	0.72	0.028	8	J outer only
RG179B/U	0.128	0.72	0.028	8	J outer only
RG213/U	0.415	2.54	0.100	10	K
RG214/U	0.429	2.54	0.100	10	K
RG223/U	0.213	1.69	0.067	8	A or G
RG316/U	0.128	0.72	0.028	8	J outer only
RG400/U	0.213	1.69	0.067	8	A or G

AVW New Zealand sales@avw.co.nz
 AVW Australia sales@avw.com.au